


# SHOE BOX / WALL PACK



## Ballast Bypass—Internal Driver

TYPE B

- ▶ All models rotate easily once secured tightly in sockets
- ▶ Pinpoint directional light so no lumens are lost in the box



All models have Type V optics unless otherwise noted



Models 8089 thru 8091 have support feet

## Ballast Compatible—Plug 'n Play

TYPE A

- ▶ Compatible with pulse or probe start magnetic metal halide ballasts
- ▶ Easiest to install—simply screw into existing socket



# SHOE BOX / WALL PACK



## SPECIFICATIONS


### Ballast Bypass | TYPE B

DESCRIPTION	120-277V	347V	LUMENS	REPLACES	LED POWER	BASE	CCT	UL LISTED	CLASSIFIED	DIMENSIONS
<b>LED-8086E G4 30W</b>	LED-8086E30-G4	LED-8086E30C-G4	2800	70W	20W	E26 Edison	3000K	✓	✓	5.5" x 3"
	LED-8086E40-G4	LED-8086E40C-G4	2800				4000K	✓	✓	
	LED-8086E50-G4	LED-8086E50C-G4	2880				5000K	✓	✓	
<b>LED-8087E G4 30W</b>	LED-8087E30-G4		3534	100W	30W	E26 Edison	3000K	✓	✓	5.5" x 3"
	LED-8087E40-G4	LED-8087E40C-A	4260				4000K	✓	✓	
	LED-8087E57-G4	LED-8087E57C-A	4255				5000K	✓	✓	
<b>LED-8087M G4 30W</b>	LED-8087M30-G4		3534	100W	30W	E39 Mogul	3000K	✓	✓	6.7" x 3"
	LED-8087M40-G4	LED-8087M40C-A	4260				4000K	✓	✓	
	LED-8087M57-G4	LED-8087M57C-A	4255				5000K	✓	✓	
<b>LED-8088E G4 50W</b>	LED-8088E30-G4	LED-8088E30C-G4	6915	175W	50W	E26 Edison	3000K	✓	✓	7.9" x 3.8"
	LED-8088E40-G4	LED-8088E40C-G4	6460				4000K	✓	✓	
	LED-8088E50-G4	LED-8088E50C-G4	7250				5000K	✓	✓	
<b>LED-8088M G4 50W</b>	LED-8088M30-G4	LED-8088M30C-G4	6915	175W	50W	EX39 Mogul	3000K	✓	✓	8.5" x 3.8"
	LED-8088M40-G4	LED-8088M40C-G4	6460				4000K	✓	✓	
	LED-8088M50-G4	LED-8088M50C-G4	7250				5000K	✓	✓	
<b>LED-8089M G5 80W</b>	LED-8089M30-G5	LED-8089M30C-G5	10670	250W	80W	EX39 Mogul	3000K	✓	✓	8.3" x 4.3"
	LED-8089M40-G5	LED-8089M40C-G5	10760				4000K	✓	✓	
	LED-8089M50-G5	LED-8089M50C-G5	10850				5000K	✓	✓	
<b>LED-8090M G4 110W</b>	LED-8090M30-G4	LED-8090M30C-G4	15745	400W	110W	EX39 Mogul	3000K	✓	✓	11.4" x 4.3"
	LED-8090M40-G4	LED-8090M40C-G4	15430				4000K	✓	✓	
	LED-8090M50-G4	LED-8090M50C-G4	14570				5000K	✓	✓	
<b>LED-8090M G4-T3 110W</b>	LED-8090M40-G4-T3	LED-8090M40C-G4-T3	12630	400W	110W	EX39 Mogul	4000K	✓	✓	11.4" x 4.3"
	LED-8090M50-G4-T3	LED-8090M50C-G4-T3	12840				5000K	✓	✓	
<b>LED-8090M G4-T4 110W</b>	LED-8090M40-G4-T4	LED-8090M40C-G4-T4	12165	400W	110W	EX39 Mogul	4000K	✓	✓	11.4" x 4.3"
	LED-8090M50-G4-T4	LED-8090M50C-G4-T4	12780				5000K	✓	✓	
<b>LED-8090M G4-OCC 110W</b>	LED-8090M40-G4-OCC	LED-8090M40C-G4-OCC	15430	400W	110W	EX39 Mogul	4000K	✓	✓	11.4" x 4.3"
	LED-8090M50-G4-OCC	LED-8090M50C-G4-OCC	14570				5000K	✓	✓	
<b>LED-8090M G4-HV 110W</b>	LED-8090M30-G4-HV		14620	400W	110W	EX39 Mogul	3000K	✓	✓	11.4" x 4.3"
	LED-8090M40-G4-HV		15180				4000K	✓	✓	
	LED-8090M50-G4-HV		15390				5000K	✓	✓	
<b>LED-8091M 320W</b>	LED-8091M30		43090	1000W	320W	EX39 Mogul	3000K	✓	✓	4.5" x 11.2" LED PANEL 8.9" x 12.6"
	LED-8091M40		43380				4000K	✓	✓	
	LED-8091M50		44610				5000K	✓	✓	
<b>LED-8091M HV 320W</b>	LED-8091M30-HV		43090	1000W	320W	EX39 Mogul	3000K	✓	✓	4.5" x 11.2" LED PANEL 8.9" x 12.6"
	LED-8091M40-HV		43380				4000K	✓	✓	
	LED-8091M50-HV		44610				5000K	✓	✓	

>80 CRI • 50,000 HOUR RATED LIFE • 5 YEAR WARRANTY



ON ALL MODELS



Step-down transformers available for 480V applications

see page 2

### Ballast Compatible | TYPE A

DESCRIPTION	MODEL #	LUMENS	REPLACES	LED POWER	BASE	CCT	UL LISTED	DIMENSIONS
<b>LED-8088E 50W</b>	LED-8088E40-MHBC	5188	250W	50W	E26 Edison	4000K	✓	7.9" x 3.8"
	LED-8088E57-MHBC	6282				5700K	✓	
<b>LED-8088M 50W</b>	LED-8088M40-MHBC	5188	250W	50W	E39 Mogul	4000K	✓	8.5" x 3.8"
	LED-8088M57-MHBC	6282				5700K	✓	
<b>LED-8089M 80W</b>	LED-8089M40-MHBC	7941	320W	80W	E39 Mogul	4000K	✓	11.4" x 4.3"
	LED-8089M50-MHBC	7635				5000K	✓	
<b>LED-8090M 120W</b>	LED-8090M40-MHBC	9929	400W	120W	E39 Mogul	4000K	✓	11.4" x 4.3"
	LED-8090M50-MHBC	10810				5000K	✓	

VOLTAGE: MH BALLAST ONLY • >80 CRI • 50,000 HOUR RATED LIFE • 5 YEAR WARRANTY

Utility Patent Pending  
14/710,301